

Wire Sorter/Wall Scanner



USA Patent
5627474

DE Patent
4417351235

TELtest Wire Sorter for 12 lines

Key Functions

- Wire Sorter Set for fast detection of up to 160 lines (possible with several signal transmitters)
- Standard signal transmitter identifies up to 12 lines
- Clear indication of short circuits, open circuits, or interruptions
- Integrated continuity tester

General Information

- Set comprising of a transmitter and a receiver in a handy carrying case
- Transmitter is supplied by receiver
- Simultaneous indication of 2 lines
- Indication of short circuits, interruptions, mixed wires, earth and ground connection
- Applicable up to 10 kΩ...test circuit resistance and a line capacity of up to 1 μF

Special Features

- Time consuming «beeping» and «belling out» with the help of a second person is now a thing of the past
- No reference line required

Technical Data

Display	LED, 2x7-Segment-Display
Maximum line Resistance (Line Capacity)	10 kΩ (1μF)
Maximum Line Length	10 km (for telecommunication cable)
Power Supply	1 x 9 V, IEC 6LR61 (Receiver)
Dimensions	59 x 79 x 15 mm (Transmitter), 64 x 132 x 35 mm (Receiver)
Weight	85 g (Transmitter) 180 g (Receiver)

Scope of Supply:

- 1 pc Transmitter (for 12 Lines)
- 1 pc Receiver
- 1 pc Battery 9V, IEC 6LR61
- 1 pc Carrying Case
- 12 pc Crocodile Clamps
- 1 pc Instruction Manual

Order Information:

Description	Cat. No.
Wire Sorter Code "1"	2/12